



ENERGY STAR CERTIFIED

# Electric Vehicle Chargers AC

## Pando Electric - Pando 001 Smart Outlet : Pando 001I

### Specifications

<b>Brand Name:</b>	Pando Electric
<b>Model Name:</b>	Pando 001 Smart Outlet
<b>Model Number:</b>	Pando 001I
<b>ENERGY STAR Unique ID:</b>	3943137
<b>ENERGY STAR Partner:</b>	Pando Electric Inc.
<b>Product Type:</b>	Level 2
<b>Input Voltage (V):</b>	240.0
<b>Max Nameplate Output Current (A):</b>	40.0
<b>Maximum Output Power (kW):</b>	9.6
<b>Number of Outputs:</b>	1
<b>Maximum Output Cord Length (ft.):</b>	0
<b>Output Cord Gauge (AWG):</b>	0
<b>Maximum (100%) Measured Luminance of the High Res Display (candelas per m2):</b>	0.0
<b>Automatic Brightness Control (ABC) Capable?:</b>	No
<b>Connected Capable:</b>	No
<b>Network Connection Types Available:</b>	Wi-Fi or Gigabit Ethernet
<b>Screen Area, if EVSE has high res display (in2):</b>	0.0
<b>Auxiliary Product Features:</b>	None
<b>15 A Operation Mode Test: Total Loss (watts):</b>	25.35
<b>30 A Operation Mode Test: Total Loss (watts):</b>	61.54
<b>4 A Operation Mode Test: Total Loss (watts):</b>	9.08
<b>Full Current Operation Mode Test: Total Loss (watts):</b>	108.27
<b>Idle Mode Input Power (watts):</b>	8.14
<b>Idle Mode Power Factor:</b>	0.36
<b>Idle Mode Total Allowance (watts):</b>	21.0
<b>No Vehicle Mode Input Power (watts):</b>	0.75
<b>No Vehicle Mode Power Factor:</b>	0.2
<b>No Vehicle Mode Total Allowance (watts):</b>	5.0
<b>Partial On Mode Input Power (watts):</b>	0.76
<b>Partial On Mode Power Factor:</b>	0.12
<b>Partial On Mode Total Allowance (watts):</b>	5.0
<b>Date Certified:</b>	2025-01-21

<b>Date Available on Market:</b>	2025-01-21
<b>Markets:</b>	United States, Canada
<b>ENERGY STAR Certified:</b>	Yes

**Captured On:**  
04/16/2026